

# Transport Window for Bunching Beams in a Final Stage of Heavy Ion Inertial Fusion

Takashi KIKUCHI, Mitsuo NAKAJIMA and Kazuhiko HORIOKA




Tokyo Institute of Technology, Department of Energy Sciences

International Workshop on Recent Progress of Induction Accelerators  
(RPIA2002), October 29-31, 2002, Tsukuba, Japan

## ● Heavy Ion Inertial Fusion

➡ Intense Heavy Ion Beam ( $\sim 10\text{GeV}$   $\sim 10\text{ns}$   $\sim 100\text{kA}$ )  
Generation & Transport are required for effective implosion.

Accelerated Heavy Ion Beam  Final Beam Bunching




Beam Irradiation for Implosion

Researches: \_\_\_\_\_


- Dynamics of Bunching Beam
- Bunching Beam Transportability in Phase Advancing Condition

# Heavy Ion Beam Bunching by Induction LINAC


Apply Bunching Voltage at each Gap



Induction buncher consists of periodic lattice, acceleration gaps & FODO quadrupole.



apply to beam



Beam head is decelerated  
Beam tail is accelerated



Head & tail velocities are modulated.  
 $\Delta\beta/\beta$  indicates Velocity Tilt.



Beam bunch becomes short during transport.

## Head-to-Tail Velocity Tilt for Bunch Compression

▶ Transverse Mismatch in terms of Quadrupole Lens

- Envelope Oscillation
- Resonance Instability



*Beam Transport Instability*

Prediction ▶ Resonance Effect by Phase Advance Modulation



Verify Simple Estimation of Instability  
using Particle-Core Model

# Beam Parameters

---

---

Ion Species	Pb <sup>1+</sup> (207.2 amu)
Ion Number	2.5x10 <sup>15</sup>
Total Charge	0.4mC
Pulse Duration	250ns ⇒ 10ns
Total Beam Current	1.6kA ⇒ 40kA
Beam Number	4
Current per Beam	400A ⇒ 10kA
Particle Energy	10GeV ( $\beta \sim 0.31$ )
Longitudinal Beam Length	23m ⇒ 0.9m

---

---


Parameters in final stage of HIF driver system

Bunch Compression Ratio = 25

by J.J. Barnard, *et al.*, Physics of Fluid B 5, 2698 (1993).


# Envelope Calculation Result with Bunching

## ▶ Longitudinal Behavior



Bunching voltages apply velocity tilt to beam, bunch compression is caused.



## ▶ Transverse Behavior



Beam bunching causes current (perveance) increase.

➡ Radius Expansion

# Core/Particle Resonance




$$\omega_{\text{core}} / \omega_{\text{particle}} = \text{integer}$$


Halo formation, larger orbit of particle, chaotic behavior, etc. are induced by resonance.

by J.-M. Lagniel, *Nucl. Instrum. Methods Phys. Res.* **A345** (1994) 46.

# Poincaré Maps



Larger Orbit  
by Resonance




Resonance reentrance  
due to  $\Delta\beta/\beta$

**Particle Loss & Halo Formation**

# Expression of Phase Advance in FODO Lattice

from Transfer Matrix

$$\cos \sigma_0 = \cos \theta \cosh \theta + \frac{L}{\ell} \theta (\cos \theta \sinh \theta - \sin \theta \cosh \theta) - \frac{1}{2} \left( \frac{L}{\ell} \right)^2 \theta^2 \sin \theta \sinh \theta$$



$\sigma_0$  : Phase Advance without Space Charge [deg]

$\theta$  : Focusing Strength of Lens [rad]

$L$  : Length of Drift Space (O in FODO) [m]

$\ell$  : Length of Focusing Space (F or D in FODO)

$$k = \left( \frac{\theta}{\ell} \right)^2$$

→ Calculate  $\sigma_0$

$\sigma$  : Phase Advance Depressed by Space Charge

$$\cos \sigma = \cos \sigma_0 + 2K \left( \frac{\ell + L}{\bar{a}} \right)^2$$

$$\bar{a}^2 = \frac{2\varepsilon_t (\ell + L)}{\sin \sigma}$$

Average Beam Radius

→ Estimate  $\sigma$

# Beam Envelope Calculation

$$X \equiv X(s) \quad Y \equiv Y(s) \quad Z \equiv Z(s)$$

$s$  : Transport Distance

Transverse Envelope Equation (K-V Distribution)

$$\left. \begin{aligned} \frac{d^2 X}{ds^2} &= -\tilde{k}_t X + \frac{2\tilde{K}}{X+Y} + \frac{\epsilon_t^2}{X^3} \\ \frac{d^2 Y}{ds^2} &= \tilde{k}_t Y + \frac{2\tilde{K}}{X+Y} + \frac{\epsilon_t^2}{Y^3} \end{aligned} \right\} \leftarrow \left\{ \begin{aligned} \tilde{k}_t &\propto \frac{1}{\tilde{\beta} \tilde{\gamma}} \\ \tilde{K} &\propto \frac{1}{\tilde{\beta}^2 \tilde{\gamma}^3} \end{aligned} \right. \text{ modulated by } \Delta\beta/\beta$$

$k_t$  : Transverse Focusing Force  
 $K$  : Transverse Perveance

Longitudinal Envelope Equation


$$\frac{d^2 Z}{ds^2} = -k_z + \frac{K_L}{Z^2} + \frac{\epsilon_{zz'}^2}{Z^3} = 0$$

$k_z$  : Longitudinal Focusing Force  
 $K_L$  : Longitudinal Perveance



***Velocity Tilt induces Beam Envelope Mismatch***

# Transport Window Shrinking with Compression




▶ For Avoiding the Resonance Conditions ...


▶ Transport Window becomes small with longitudinal compression ( $K$  increase).



It is difficult that entire beam stability is maintained during compression.




# Phase Advance Dynamics with Compression



► The phase advance goes off Transport Window during compression.


# Particle-Core Model (PCM) Calculation




Test Particle Equation in PCM

$$\frac{d^2 x}{ds^2} = -\tilde{k}_x x + \begin{cases} \frac{2\tilde{K}}{X(X+Y)} x & (|x| \leq X) \\ \frac{\text{sgn}(x) \cdot 2\tilde{K}}{|x| + \sqrt{x^2 + Y^2 - X^2}} & (|x| > X) \end{cases}$$

# Poincaré plot at each slice with compression




PCM calculations are carried out at each sliced position. Each Poincaré plot is shown in 




From relation between velocity tilt & perveance, resonance effect is appeared at near center, rather than beam head.

# Summary


 Resonance reentrance due to  $\Delta\beta/\beta$



Instability Growth

 Simple Prediction of Phase Advance Modulation

Resonance Reentrance & Envelope Mismatch

 decide Transport Window for Bunching Beam

Transport Window changes with Longitudinal Compression